

Ringling current - internal bell WK 952 - ringing rod bell -



The volume-adjustable sound rod bell with 1 mF condensator is used as additional signalling for telephones in indoor rooms.

Possible application areas:

- telecommunication
- industry
- end user
- for use in the telecommunication network

Features:

- volume adjustable
- surface version

Technical data:

volume (small reverberent room)
operating voltage
frequency range
current consumption at 50 V ~ 25 Hz / 50 Hz
d.c. resistance
impedance at 800 Hz
housing made from thermoplastic
polarised system
radio noise free
weight
colour
dimensions L x W x H approx. in mm

Part no.:

60124

Authorisations:

- ZZF-authorisation 119/021
- CE-marking

Applications:

- for indoor rooms
- for additional signalling
in rooms without a telephone

≥ 75 dB (A)
15 - 80 V ~
15 - 50 Hz
approx. 12 mA
1500 W
≥ 20 kW

280 g
ivory
115 x 80 x 39