A.C. outside bell WK 971



The a.c. outside bell WK 971 is an additional weatherproof electro-mechanical signal device for voltagest. It is intended as additional signalling in the private and industrial area.

Possible application areas:

- railways
- mountain railways / funicular railways / ski-lifts
- industry
- military engineering
- rescue
- security

Features:

- weatherproof
- for robust outside use
- for additional ringing signalling
- two-tone sound
- secure against cross poling
- separate connection chamber

Technical data:

110 - 230 volt
volume at 1 m distance
splash-proof, type of protection
housing made from glass fibre reinforced plastic
(polycarbonate)
bell shells made from die cast light metal
polarised system
radio noise free
weight
colour
dimensions L x W x H approx. in mm

Part no.:

60122

Autorisations:

- CE-marking

Applications:

- in loud rooms
- in damp rooms
- for outside
- for indoor rooms

Note:

 during connection to a similar telephone system becomes connecting relay AR 102 (articles No. 60604) needed

<u>></u> 90 dB (A) IP 43

1000 g pebble grey similar to RAL 7032 $208 \times 170 \times 115$



signaltechnik**sprenger**gmbh

D - 95119 Naila Deutschland phone +49 92 82 / 9638-400 fax +49 92 82 / 9638-430 e-mail: info@sts-sprenger.de www.sts-sprenger.de

Zum Kugelfang 24